

## Fuse Reducers and Dummy "Neutrals"



### Fuse Reducers for Class J Dimension Fuses: LPJ, DFJ, JKS

Catalog Numbers

Catalog Numbers (Pair) Reducer No.	Fuse Amp Size Range	Equipment/Fuseblock Amp Size
J-63	1-30	60
J-13	1-30	100
J-16	35-60	100
J-26	35-60	200†
J-21	70-100	200†
J-41	70-100	400†
J-42	110-200	400†
J-62	110-200	600†
J-64	225-400	600†

†Not for Bolt-on Applications.

### Fuse Reducers for Class R Dimension Fuses: FRN-R, LPN-RK, FRS-R, LPS-RK, KTN-R, KTS-R

UL Listed File E12853

Catalog Numbers

Catalog Numbers (Pairs)		Fuse Amp Size Range	Equipment/Fuseblock Amp Size
Voltages			
250V	600V		
NO.263-R	NO.663-R	1-30	60
NO.213-R	NO.216-R	1-30	100
NO.216-R	NO.616-R	35-60	100
NO.226-R	NO.626-R	35-60	200
NO.2621-R*	NO.2621-R	70-100	200
NO.2641-R	NO.2641-R	70-100	400
NO.242-R	NO.642-R	110-200	400
NO.2661-R	NO.2661-R	70-100	600
NO.2662-R	NO.2662-R	110-200	600
NO.2664-R**	NO.2664-R**	225-400	600

\*Reducer NO.2621-R does not apply to LPN-RK-70SP to LPN-RK-100SP Fuses.

\*\*Single reducer only (pair not required).

### Fuse Reducers for Class H & K Dimension Fuses: NON, REN, NOS, RES

UL Listed File E12853

Catalog Numbers

Catalog Numbers. (Pairs)		Fuse Amp Size Range	Equipment/Fuseblock Amp Size
250V Reducer	600V Reducer		
NO.263	NO.663	1-30	60
NO.213	NO.216	1-30	100
NO.216	NO.616	35-60	100
NO.226	NO.626	35-60	200
NO.2621	NO.2621	70-100	200
NO.2641	NO.2641	70-100	400
NO.2642	NO.2642	110-200	400

Data Sheet: 1118



### Dummy Fuse "Neutrals" (These are not fuses)

Catalog Numbers

Catalog Numbers	Fuse Equivalent		
	Voltage	Dimension	Fuse Amp Size Range
NNB	—	<sup>13</sup> / <sub>32</sub> " x 1 1/2"	—
NNB-R	—	Class CC	—
NNC	—	1/4" x 1 1/4"	—
NTN-R-30	250	R/H	1-30
NTN-R-60	250	R/H	35-60
NTN-R-100	250	R/H	70-100
NTN-R-200	250	R/H	110-200
NTN-R-400	250	R/H	225-400
NTS-R-30	600	R/H	1-30
NTS-R-60	600	R/H	35-60
NTS-R-100	600	R/H	70-100
NTS-R-200	600	R/H	110-200
NTS-R-400	600	R/H	225-400
NTS-R-600	600	R/H	450-600