

## Compact Fluorescent

### Applications:

**Perfect for most applications:** Use where a standard incandescent is used.

- + Table Lamps
- + Floor Lamps
- + Ceiling Fixtures
- + Wall Sconces
- + Vanities
- + Track Lighting



### Features and Benefits:

- Long life, 10,000 hour average rated life – SpringLamps®
- 8,000 hour average rated life – globes/a-lamp/floodlights
- Lasts 9 years, based on 3 hours use per day – SpringLamps®
- Lasts 7 years, based on 3 hours use per day – globes/a-lamp/floodlights
- Replace less often, ideal for hard to reach places
- Lower maintenance costs for lamp replacements
- Saves up to 75% in energy costs compared to similar light output incandescent lamps
- Available in the following color temperatures: 2700K, 3500K, 4100K, 5000K and 6500K
- Quick run-up time
- Medium base and compact height fits anywhere a standard incandescent fits
- Instant start, flicker free
- End of Life logic guards against violent failures
- World class phosphor insures high lumen output and excellent lumen maintenance
- Up to 23 watts approved for enclosed fixtures



ISO 9002  
CERTIFIED

RoHS  
COMPLIANT

Catalog Number

Notes

Type



### Specifications: (at full brightness)

|                               |                            |
|-------------------------------|----------------------------|
| End of Life Protection        | Yes                        |
| Ballast Type                  | Electronic                 |
| Starting Method               | Modified Rapid Start       |
| Input Line Voltage            | 120VAC                     |
| Input Line Frequency          | 50/60HZ                    |
| Lamp Life (rated)             | 10,000 Hours / 8,000 Hours |
| Color Temperature             | 2700°K                     |
| Color Rendering Index         | 82                         |
| Minimum Starting Temperature  | -20°F, -29°C               |
| Maximum Operating Temperature | 160°F, 71°C                |
| U.L. / C.U.L. Listed          | Yes                        |
| FCC Compliance                | 47 C.F.R. Part 18          |
| Lamp Operating Frequency      | 45 KHZ                     |
| Lamp Current Crest Factor     | <1.60                      |
| Max. Open Circuit Voltage     | 600V                       |
| Total Harmonic Distortion     | <150%                      |
| Power Factor Rated            | >.50                       |

### Special Application Notes:

Up to 23 watt is UL approved for totally enclosed fixtures.

Use a 27 watt in an open recessed can.

Do not use more than 2 bulbs in an enclosed fixture.

If fixture is manufactured for incandescents, use no higher than the CFL equivalent wattage, as shown on chart.



For the most up-to-date specs, please visit [www.tcp.com](http://www.tcp.com)



## Meeting Your Needs.

SpringLight™ is our basic standard CFL lineup which includes half SpringLamps® and standard floods. These high quality lamps are reasonably priced, designed to fit your budget, and are available in a variety of pack sizes from 1-packs to contractor packs and pallet programs.

| Item Number                         | Item Description               | Unit/Ballast Watts | Incandescent Comparison (Watts) | Initial Lumens | CCT (Kelvin) | CRI | MOL/Height (Inches) | Diameter/Width (Inches) | Input Line Current | Case Quantity |
|-------------------------------------|--------------------------------|--------------------|---------------------------------|----------------|--------------|-----|---------------------|-------------------------|--------------------|---------------|
| <b>SPRINGLIGHT™ SPRINGLAMPS®</b>    |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 801009                              | 9W SpringLamp 27K              | 9                  | 40                              | 500            | 2700         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 80100935                            | 9W SpringLamp 35K              | 9                  | 40                              | 550            | 3500         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 80100941                            | 9W SpringLamp 41K              | 9                  | 40                              | 550            | 4100         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 80100950                            | 9W SpringLamp 50K              | 9                  | 40                              | 500            | 5000         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 801014                              | 14W SpringLamp 27K             | 14                 | 60                              | 900            | 2700         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 8010143                             | 14W SpringLamp 27K 3PK         | 14                 | 60                              | 900            | 2700         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101435                            | 14W SpringLamp 35K             | 14                 | 60                              | 900            | 3500         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101441                            | 14W SpringLamp 41K             | 14                 | 60                              | 900            | 4100         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 801014413                           | 14W SpringLamp 41K 3PK         | 14                 | 60                              | 900            | 4100         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101450                            | 14W SpringLamp 50K             | 14                 | 60                              | 850            | 5000         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101465                            | 14W SpringLamp 65K             | 14                 | 60                              | 850            | 6500         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 801019                              | 19W SpringLamp 27K             | 19                 | 75                              | 1225           | 2700         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 8010193                             | 19W SpringLamp 27K 3PK         | 19                 | 75                              | 1225           | 2700         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101935                            | 19W SpringLamp 35K             | 19                 | 75                              | 1225           | 3500         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101941                            | 19W SpringLamp 41K             | 19                 | 75                              | 1200           | 4100         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 801019413                           | 19W SpringLamp 41K 3PK         | 19                 | 75                              | 1200           | 4100         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101950                            | 19W SpringLamp 50K             | 19                 | 75                              | 1200           | 5000         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101965                            | 19W SpringLamp 65K             | 19                 | 75                              | 1200           | 6500         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 801023                              | 23W SpringLamp 27K             | 23                 | 100                             | 1600           | 2700         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 8010233                             | 23W SpringLamp 27K 3PK         | 23                 | 100                             | 1600           | 2700         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102335                            | 23W SpringLamp 35K             | 23                 | 100                             | 1600           | 3500         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102341                            | 23W SpringLamp 41K             | 23                 | 100                             | 1600           | 4100         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 801023413                           | 23W SpringLamp 41K 3PK         | 23                 | 100                             | 1600           | 4100         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102350                            | 23W SpringLamp 50K             | 23                 | 100                             | 1500           | 5000         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102365                            | 23W SpringLamp 65K             | 23                 | 100                             | 1500           | 6500         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 801027                              | 27W SpringLamp 27K             | 27                 | 100                             | 1750           | 2700         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 8010273                             | 27W SpringLamp 27K 3PK         | 27                 | 100                             | 1750           | 2700         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102735                            | 27W SpringLamp 35K             | 27                 | 100                             | 1750           | 3500         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102741                            | 27W SpringLamp 41K             | 27                 | 100                             | 1750           | 4100         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 801027413                           | 27W SpringLamp 41K 3PK         | 27                 | 100                             | 1750           | 4100         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102750                            | 27W SpringLamp 50K             | 27                 | 100                             | 1750           | 5000         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102765                            | 27W SpringLamp 65K             | 27                 | 100                             | 1750           | 6500         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 801032                              | 32W SpringLamp 27K             | 32                 | 125                             | 2100           | 2700         | 82  | 6.0                 | 2.8                     | .53A               | 12            |
| 80103241                            | 32W SpringLamp 41K             | 32                 | 125                             | 2000           | 4100         | 82  | 6.0                 | 2.8                     | .53A               | 12            |
| 801042                              | 42W SpringLamp 27K             | 42                 | 150                             | 2750           | 2700         | 82  | 7.0                 | 2.8                     | .70A               | 12            |
| 80104241                            | 42W SpringLamp 41K             | 42                 | 150                             | 2650           | 4200         | 82  | 7.0                 | 2.8                     | .70A               | 12            |
| <b>SPRINGLIGHT™ REFLECTOR LAMPS</b> |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 802014                              | 14w R20 Flood SpringLamp       | 14                 | 50                              | 495            | 2700         | 82  | 4.3                 | 2.5                     | .23A               | 12            |
| 803014                              | 14w R30 Flood SpringLamp       | 14                 | 65                              | 645            | 2700         | 82  | 5.4                 | 3.7                     | .23A               | 12            |
| 8030142                             | 14w R30 Flood SpringLamp 2PK   | 14                 | 65                              | 645            | 2700         | 82  | 5.4                 | 3.7                     | .23A               | 12            |
| 804023                              | 23w R40 Flood SpringLamp       | 23                 | 85                              | 1150           | 2700         | 82  | 6.1                 | 4.8                     | .38A               | 12            |
| 805023                              | 23w Par38 Flood SpringLamp     | 23                 | 90                              | 1200           | 2700         | 82  | 6.2                 | 4.8                     | .38A               | 12            |
| 8050232                             | 23w Par38 Flood SpringLamp 2PK | 23                 | 90                              | 1200           | 2700         | 82  | 6.2                 | 4.8                     | .38A               | 12            |
| <b>SPRINGLIGHT™ GLOBES</b>          |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 8060093                             | 9w G25 Globe SpringLamp 3PK    | 9                  | 40                              | 495            | 2700         | 82  | 4.3                 | 3.1                     | .15A               | 12            |
| 8060143                             | 14w G25 Globe SpringLamp 3PK   | 14                 | 60                              | 800            | 2700         | 82  | 4.3                 | 3.1                     | .23A               | 12            |
| <b>SPRINGLIGHT™ A-LAMPS</b>         |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 8070093                             | 9w A-Lamp SpringLamp 3PK       | 9                  | 40                              | 450            | 2700         | 82  | 4.1                 | 2.2                     | .15A               | 12            |
| 8070143                             | 14w A-Lamp SpringLamp 3PK      | 14                 | 60                              | 800            | 2700         | 82  | 4.3                 | 3.1                     | .23A               | 12            |
| <b>SPRINGLIGHT™ MULTI-PACKS</b>     |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 8011412                             | 14w SpringLamp 12PK            | 14                 | 60                              | 900            | 2700         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 8011912                             | 19w SpringLamp 12PK            | 19                 | 75                              | 1225           | 2700         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 8012312                             | 23w SpringLamp 12PK            | 23                 | 100                             | 1600           | 2700         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 8012712                             | 27w SpringLamp 12PK            | 27                 | 100                             | 1750           | 2700         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 801R30146                           | 14w R30 SpringLamp 6PK         | 14                 | 65                              | 645            | 2700         | 82  | 5.4                 | 3.7                     | .23A               | 12            |



SpringLamp



R20 Flood



R30 Flood



R40 Flood



PAR38 Flood



G25 Globe



A-Lamp

For the most up-to-date specs, please visit [www.tcp.com](http://www.tcp.com)



## Compact Fluorescent

### Applications:

**Perfect for most applications:** Use where a standard incandescent is used.

- + Table Lamps
- + Floor Lamps
- + Ceiling Fixtures
- + Wall Sconces
- + Vanities
- + Track Lighting



### Features and Benefits:

- Long life, 10,000 hour average rated life – SpringLamps®
- 8,000 hour average rated life – globes/a-lamp/floodlights
- Lasts 9 years, based on 3 hours use per day – SpringLamps®
- Lasts 7 years, based on 3 hours use per day – globes/a-lamp/floodlights
- Replace less often, ideal for hard to reach places
- Lower maintenance costs for lamp replacements
- Saves up to 75% in energy costs compared to similar light output incandescent lamps
- Available in the following color temperatures: 2700K, 3500K, 4100K, 5000K and 6500K
- Quick run-up time
- Medium base and compact height fits anywhere a standard incandescent fits
- Instant start, flicker free
- End of Life logic guards against violent failures
- World class phosphor insures high lumen output and excellent lumen maintenance
- Up to 23 watts approved for enclosed fixtures



ISO 9002  
CERTIFIED

**RoHS**  
COMPLIANT

Catalog Number

Notes

Type



### Specifications: (at full brightness)

|                               |       |                            |
|-------------------------------|-------|----------------------------|
| End of Life Protection        | ..... | Yes                        |
| Ballast Type                  | ..... | Electronic                 |
| Starting Method               | ..... | Modified Rapid Start       |
| Input Line Voltage            | ..... | 120VAC                     |
| Input Line Frequency          | ..... | 50/60HZ                    |
| Lamp Life (rated)             | ..... | 10,000 Hours / 8,000 Hours |
| Color Temperature             | ..... | 2700°K                     |
| Color Rendering Index         | ..... | 82                         |
| Minimum Starting Temperature  | ..... | -20°F, -29°C               |
| Maximum Operating Temperature | ..... | 160°F, 71°C                |
| U.L. / C.U.L. Listed          | ..... | Yes                        |
| FCC Compliance                | ..... | 47 C.F.R. Part 18          |
| Lamp Operating Frequency      | ..... | 45 KHZ                     |
| Lamp Current Crest Factor     | ..... | <1.60                      |
| Max. Open Circuit Voltage     | ..... | 600V                       |
| Total Harmonic Distortion     | ..... | <150%                      |
| Power Factor Rated            | ..... | >.50                       |

### Special Application Notes:

Up to 23 watt is UL approved for totally enclosed fixtures.

Use a 27 watt in an open recessed can.

Do not use more than 2 bulbs in an enclosed fixture.

If fixture is manufactured for incandescents, use no higher than the CFL equivalent wattage, as shown on chart.



For the most up-to-date specs, please visit [www.tcpi.com](http://www.tcpi.com)



## Meeting Your Needs.

SpringLight™ is our basic standard CFL lineup which includes half SpringLamps® and standard floods. These high quality lamps are reasonably priced, designed to fit your budget, and are available in a variety of pack sizes from 1-packs to contractor packs and pallet programs.

| Item Number                         | Item Description               | Unit/Ballast Watts | Incandescent Comparison (Watts) | Initial Lumens | CCT (Kelvin) | CRI | MOL/Height (Inches) | Diameter/Width (Inches) | Input Line Current | Case Quantity |
|-------------------------------------|--------------------------------|--------------------|---------------------------------|----------------|--------------|-----|---------------------|-------------------------|--------------------|---------------|
| <b>SPRINGLIGHT™ SPRINGLAMPS®</b>    |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 801009                              | 9W SpringLamp 27K              | 9                  | 40                              | 500            | 2700         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 80100935                            | 9W SpringLamp 35K              | 9                  | 40                              | 550            | 3500         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 80100941                            | 9W SpringLamp 41K              | 9                  | 40                              | 550            | 4100         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 80100950                            | 9W SpringLamp 50K              | 9                  | 40                              | 500            | 5000         | 82  | 4.0                 | 1.8                     | .15A               | 12            |
| 801014                              | 14W SpringLamp 27K             | 14                 | 60                              | 900            | 2700         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 8010143                             | 14W SpringLamp 27K 3PK         | 14                 | 60                              | 900            | 2700         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101435                            | 14W SpringLamp 35K             | 14                 | 60                              | 900            | 3500         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101441                            | 14W SpringLamp 41K             | 14                 | 60                              | 900            | 4100         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 801014413                           | 14W SpringLamp 41K 3PK         | 14                 | 60                              | 900            | 4100         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101450                            | 14W SpringLamp 50K             | 14                 | 60                              | 850            | 5000         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 80101465                            | 14W SpringLamp 65K             | 14                 | 60                              | 850            | 6500         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 801019                              | 19W SpringLamp 27K             | 19                 | 75                              | 1225           | 2700         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 8010193                             | 19W SpringLamp 27K 3PK         | 19                 | 75                              | 1225           | 2700         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101935                            | 19W SpringLamp 35K             | 19                 | 75                              | 1225           | 3500         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101941                            | 19W SpringLamp 41K             | 19                 | 75                              | 1200           | 4100         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 801019413                           | 19W SpringLamp 41K 3PK         | 19                 | 75                              | 1200           | 4100         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101950                            | 19W SpringLamp 50K             | 19                 | 75                              | 1200           | 5000         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 80101965                            | 19W SpringLamp 65K             | 19                 | 75                              | 1200           | 6500         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 801023                              | 23W SpringLamp 27K             | 23                 | 100                             | 1600           | 2700         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 8010233                             | 23W SpringLamp 27K 3PK         | 23                 | 100                             | 1600           | 2700         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102335                            | 23W SpringLamp 35K             | 23                 | 100                             | 1600           | 3500         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102341                            | 23W SpringLamp 41K             | 23                 | 100                             | 1600           | 4100         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 801023413                           | 23W SpringLamp 41K 3PK         | 23                 | 100                             | 1600           | 4100         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102350                            | 23W SpringLamp 50K             | 23                 | 100                             | 1500           | 5000         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 80102365                            | 23W SpringLamp 65K             | 23                 | 100                             | 1500           | 6500         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 801027                              | 27W SpringLamp 27K             | 27                 | 100                             | 1750           | 2700         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 8010273                             | 27W SpringLamp 27K 3PK         | 27                 | 100                             | 1750           | 2700         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102735                            | 27W SpringLamp 35K             | 27                 | 100                             | 1750           | 3500         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102741                            | 27W SpringLamp 41K             | 27                 | 100                             | 1750           | 4100         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 801027413                           | 27W SpringLamp 41K 3PK         | 27                 | 100                             | 1750           | 4100         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102750                            | 27W SpringLamp 50K             | 27                 | 100                             | 1750           | 5000         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 80102765                            | 27W SpringLamp 65K             | 27                 | 100                             | 1750           | 6500         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 801032                              | 32W SpringLamp 27K             | 32                 | 125                             | 2100           | 2700         | 82  | 6.0                 | 2.8                     | .53A               | 12            |
| 80103241                            | 32W SpringLamp 41K             | 32                 | 125                             | 2000           | 4100         | 82  | 6.0                 | 2.8                     | .53A               | 12            |
| 801042                              | 42W SpringLamp 27K             | 42                 | 150                             | 2750           | 2700         | 82  | 7.0                 | 2.8                     | .70A               | 12            |
| 80104241                            | 42W SpringLamp 41K             | 42                 | 150                             | 2650           | 4200         | 82  | 7.0                 | 2.8                     | .70A               | 12            |
| <b>SPRINGLIGHT™ REFLECTOR LAMPS</b> |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 802014                              | 14w R20 Flood SpringLamp       | 14                 | 50                              | 495            | 2700         | 82  | 4.3                 | 2.5                     | .23A               | 12            |
| 803014                              | 14w R30 Flood SpringLamp       | 14                 | 65                              | 645            | 2700         | 82  | 5.4                 | 3.7                     | .23A               | 12            |
| 8030142                             | 14w R30 Flood SpringLamp 2PK   | 14                 | 65                              | 645            | 2700         | 82  | 5.4                 | 3.7                     | .23A               | 12            |
| 804023                              | 23w R40 Flood SpringLamp       | 23                 | 85                              | 1150           | 2700         | 82  | 6.1                 | 4.8                     | .38A               | 12            |
| 805023                              | 23w Par38 Flood SpringLamp     | 23                 | 90                              | 1200           | 2700         | 82  | 6.2                 | 4.8                     | .38A               | 12            |
| 8050232                             | 23w Par38 Flood SpringLamp 2PK | 23                 | 90                              | 1200           | 2700         | 82  | 6.2                 | 4.8                     | .38A               | 12            |
| <b>SPRINGLIGHT™ GLOBES</b>          |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 8060093                             | 9w G25 Globe SpringLamp 3PK    | 9                  | 40                              | 495            | 2700         | 82  | 4.3                 | 3.1                     | .15A               | 12            |
| 8060143                             | 14w G25 Globe SpringLamp 3PK   | 14                 | 60                              | 800            | 2700         | 82  | 4.3                 | 3.1                     | .23A               | 12            |
| <b>SPRINGLIGHT™ A-LAMPS</b>         |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 8070093                             | 9w A-Lamp SpringLamp 3PK       | 9                  | 40                              | 450            | 2700         | 82  | 4.1                 | 2.2                     | .15A               | 12            |
| 8070143                             | 14w A-Lamp SpringLamp 3PK      | 14                 | 60                              | 800            | 2700         | 82  | 4.3                 | 3.1                     | .23A               | 12            |
| <b>SPRINGLIGHT™ MULTI-PACKS</b>     |                                |                    |                                 |                |              |     |                     |                         |                    |               |
| 8011412                             | 14w SpringLamp 12PK            | 14                 | 60                              | 900            | 2700         | 82  | 4.4                 | 1.8                     | .23A               | 12            |
| 8011912                             | 19w SpringLamp 12PK            | 19                 | 75                              | 1225           | 2700         | 82  | 4.4                 | 2.3                     | .31A               | 12            |
| 8012312                             | 23w SpringLamp 12PK            | 23                 | 100                             | 1600           | 2700         | 82  | 4.8                 | 2.3                     | .38A               | 12            |
| 8012712                             | 27w SpringLamp 12PK            | 27                 | 100                             | 1750           | 2700         | 82  | 5.5                 | 2.4                     | .45A               | 12            |
| 801R30146                           | 14w R30 SpringLamp 6PK         | 14                 | 65                              | 645            | 2700         | 82  | 5.4                 | 3.7                     | .23A               | 12            |



SpringLamp



R20 Flood



R30 Flood



R40 Flood



PAR38 Flood



G25 Globe



A-Lamp

For the most up-to-date specs, please visit [www.tcp.com](http://www.tcp.com)

