



# ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr.  
75964-0000, TX Nacogdoches  
Phone: 936-569-7941  
Fax: 936-560-4685



## **3BR1836L150R 3PH 150A Mlo 18/36 Cir. Al Bus Nema 3R**

*Eaton Corp*

|                  |  |
|------------------|--|
| Catalog Number   | 3BR1836L150R   |
| Manufacturer     | Eaton Corp   |
| Description      | Eaton BR Main Lug Loadcenter, No Feed-Thru Lugs, Main Lug, 150 A, C3R, Aluminum, Cover Included, Nema 3R, Metallic, 25 Kaic, BWH, Nema 3R, 36 Circuits, 18 Spaces, Four-Wire, Three-Phase, Type BR 1-Inch Breakers, 208 Y/120, 240 V, #1 Awg-300 Kcmil Cu/Al |
| Weight per unit  | 28.2 (lbs/each)  |
| Product Category | Three Phase Main Lug Load Cent   |

### **Features**

|                  |                |
|------------------|----------------|
| amperage rating  | 150            |
| Cover Type       | Cover included |
| interrupt rating | 25             |
| number of spaces | 18             |
| Phase            | 3              |
| Voltage Rating   | 208Y/120, 240V |

### **Dimensions and Weight**

|        |       |
|--------|-------|
| Depth  | 5.19  |
| Height | 25    |
| Size   | C3r   |
| Width  | 14.31 |



# ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr.  
75964-0000, TX Nacogdoches  
Phone: 936-569-7941  
Fax: 936-560-4685

## Descriptions

|                        |   |
|------------------------|---|
| Description            | 3PH 150A MLO 18/36 CIR. AL BUS NEMA 3R  |
| extra long description | ETN 3BR1836L150R 3 Ph/BR LC 150A ML   |
| Features               | Specially designed for easy installation, Eaton's BR 1-inch load centers house the branch circuit breakers and the wiring required to distribute power to individual circuits. They serve as main breaker for service entrances or as main lug when adding circuits to existing service. The main breaker protects the entire panel and can be used as a service disconnect. The branch breakers protect the wires leading to individual electrical loads such as fixtures and outlets. |
| Long Description       | Eaton BR main lug loadcenter, No feed-thru lugs, Main lug, 150 A, C3R, Aluminum, Cover included, NEMA 3R, Metallic, 25 kAIC, BWH, NEMA 3R, 36 Circuits, 18 Spaces, Four-wire, Three-phase, Type BR 1-inch breakers, 208 Y/120, 240 V, #1 AWG-300 kcmil Cu/Al  |
| Product Type           | 3 PH/BR LC 150A Mlo 18/36 CKT Al Bus N3R  |
| Special Features       | No feed-thru lugs   |

## Manufacturer Information

|                           |                |
|---------------------------|----------------|
| Brand                     | Eaton          |
| GTIN                      | 00786676441605 |
| Manufacturers Part Number | 3BR1836L150R   |
| UPC                       | 786676441605   |

## Taxonomies, Classifications, and Categories

|                      |                      |
|----------------------|----------------------|
| Category Description | LOADCENTERS & COVERS |
| Type                 | Main lug loadcenter  |

## Packaging

|                 |      |
|-----------------|------|
| Carton          | 1    |
| Weight Per each | 28.2 |

## Uses, Certifications, and Standards

|             |  |
|-------------|--|
| Application | Elec Assemblies, Panels & OEM - Electrical Assemblies, Panels and OEMs |
| standard    | UL 50, UL 67   |