

## LED T8 LAMPS

### Satco 11.5W, 4' LED T8 lamps

Direct replacement for linear fluorescent T8 lamps in existing fixtures with instant or rapid start ballasts. No rewiring required\*\*

#### Applications/ Features

- Over 40% energy savings vs standard 4' T8 systems
- All glass tube
- Direct replacement solution allows the fixture to maintain the Original UL and CSA Compliance
- Long life—50,000 hours
- Compatible with emergency ballasts\*\*
- Damp location
- c-UL-us listed
- DLC listed\*
- 5 Year warranty



#### LED Fluorescent Replacement Lamps

| Item Number | Lamp Description     | W    | CRI | Base Type  | Bm   | CCT   | Lm   | M.O.L. (Inches) | Life/Hrs. | UPC          | Pack |
|-------------|----------------------|------|-----|------------|------|-------|------|-----------------|-----------|--------------|------|
| S9934*      | 11.5T8/LED/48-830/DR | 11.5 | 82  | Med Bi-Pin | 210° | 3000K | 1700 | 48              | 50K       | 045923099342 | 10   |
| S9935*      | 11.5T8/LED/48-835/DR | 11.5 | 82  | Med Bi-Pin | 210° | 3500K | 1700 | 48              | 50K       | 045923097355 | 10   |
| S9936*      | 11.5T8/LED/48-840/DR | 11.5 | 82  | Med Bi-Pin | 210° | 4000K | 1800 | 48              | 50K       | 045923099366 | 10   |
| S9937*      | 11.5T8/LED/48-850/DR | 11.5 | 82  | Med Bi-Pin | 210° | 5000K | 1800 | 48              | 50K       | 045923099373 | 10   |

\*\*May not be compatible with all instant start, rapid start, and emergency ballasts. Visit [www.satco.com](http://www.satco.com) for an approved list.

### Satco 11.5W, 4' LED T8 lamps

Direct replacement for linear fluorescent T8 lamps in existing fixtures with instant or rapid start ballasts. No rewiring required\*\*

#### Applications/ Features

- Over 40% energy savings vs standard 4' T8 systems
- All glass tube
- Direct replacement solution allows the fixture to maintain the Original UL and CSA Compliance
- Long life—50,000 hours
- Compatible with emergency & dimming ballasts\*\*
- Damp location
- c-UL-us listed
- DLC listed\*
- 5 Year warranty



#### LED Fluorescent Replacement Lamps

| Item Number | Lamp Description        | W    | CRI | Base Type  | Bm   | CCT   | Lm   | M.O.L. (Inches) | Life/Hrs. | UPC          | Pack |
|-------------|-------------------------|------|-----|------------|------|-------|------|-----------------|-----------|--------------|------|
| S9938*      | 11.5T8/LED/48-830/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 3000K | 1700 | 48              | 50K       | 045923099380 | 10   |
| S9939*      | 11.5T8/LED/48-835/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 3500K | 1700 | 48              | 50K       | 045923099397 | 10   |
| S9940*      | 11.5T8/LED/48-840/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 4000K | 1800 | 48              | 50K       | 045923099403 | 10   |
| S9941*      | 11.5T8/LED/48-850/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 5000K | 1800 | 48              | 50K       | 045923099410 | 10   |

\*\*May not be compatible with all instant start, rapid start, dimmable, and emergency ballasts. Visit [www.satco.com](http://www.satco.com) for an approved list.

## LED T8 LAMPS

### Satco 11.5W, 4' LED T8 lamps

Direct replacement for linear fluorescent T8 lamps in existing fixtures with instant or rapid start ballasts. No rewiring required\*\*

#### Applications/ Features

- Over 40% energy savings vs standard 4' T8 systems
- All glass tube
- Direct replacement solution allows the fixture to maintain the Original UL and CSA Compliance
- Long life—50,000 hours
- Compatible with emergency ballasts\*\*
- Damp location
- c-UL-us listed
- DLC listed\*
- 5 Year warranty



#### LED Fluorescent Replacement Lamps

| Item Number | Lamp Description     | W    | CRI | Base Type  | Bm   | CCT   | Lm   | M.O.L. (Inches) | Life/Hrs. | UPC          | Pack |
|-------------|----------------------|------|-----|------------|------|-------|------|-----------------|-----------|--------------|------|
| S9934*      | 11.5T8/LED/48-830/DR | 11.5 | 82  | Med Bi-Pin | 210° | 3000K | 1700 | 48              | 50K       | 045923099342 | 10   |
| S9935*      | 11.5T8/LED/48-835/DR | 11.5 | 82  | Med Bi-Pin | 210° | 3500K | 1700 | 48              | 50K       | 045923097355 | 10   |
| S9936*      | 11.5T8/LED/48-840/DR | 11.5 | 82  | Med Bi-Pin | 210° | 4000K | 1800 | 48              | 50K       | 045923099366 | 10   |
| S9937*      | 11.5T8/LED/48-850/DR | 11.5 | 82  | Med Bi-Pin | 210° | 5000K | 1800 | 48              | 50K       | 045923099373 | 10   |

\*\*May not be compatible with all instant start, rapid start, and emergency ballasts. Visit [www.satco.com](http://www.satco.com) for an approved list.

### Satco 11.5W, 4' LED T8 lamps

Direct replacement for linear fluorescent T8 lamps in existing fixtures with instant or rapid start ballasts. No rewiring required\*\*

#### Applications/ Features

- Over 40% energy savings vs standard 4' T8 systems
- All glass tube
- Direct replacement solution allows the fixture to maintain the Original UL and CSA Compliance
- Long life—50,000 hours
- Compatible with emergency & dimming ballasts\*\*
- Damp location
- c-UL-us listed
- DLC listed\*
- 5 Year warranty



#### LED Fluorescent Replacement Lamps

| Item Number | Lamp Description        | W    | CRI | Base Type  | Bm   | CCT   | Lm   | M.O.L. (Inches) | Life/Hrs. | UPC          | Pack |
|-------------|-------------------------|------|-----|------------|------|-------|------|-----------------|-----------|--------------|------|
| S9938*      | 11.5T8/LED/48-830/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 3000K | 1700 | 48              | 50K       | 045923099380 | 10   |
| S9939*      | 11.5T8/LED/48-835/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 3500K | 1700 | 48              | 50K       | 045923099397 | 10   |
| S9940*      | 11.5T8/LED/48-840/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 4000K | 1800 | 48              | 50K       | 045923099403 | 10   |
| S9941*      | 11.5T8/LED/48-850/DR/DM | 11.5 | 82  | Med Bi-Pin | 210° | 5000K | 1800 | 48              | 50K       | 045923099410 | 10   |

\*\*May not be compatible with all instant start, rapid start, dimmable, and emergency ballasts. Visit [www.satco.com](http://www.satco.com) for an approved list.